

Hi,

Here it is the RX+TX mod for the IC-7100.

**\*\*MODS ON YOUR OWN RISC. DON'T BLAME ME!\*\***

Remove bottom and find the diode matrix.

Option (A) for TX:

1.6 – 54 MHz

68 – 74.799999 MHz

118 – 174 MHz

400 – 470 MHz

Remove 315 and place 316

**\*\* DON'T SEND TO MUCH OUT OF HAM BANDS! FILTERS AND PA WILL BE DESTROYED \*\***

Option (B) For TX:

0.1 – 199.999999 MHz

400 – 470 MHz

Remove 315 and 316

**\*\* DON'T SEND TO MUCH OUT OF HAM BANDS! FILTERS AND PA WILL BE DESTROYED \*\***

FULL RX: (0.03 – 199.999999MHz + 400 – 470MHz)

Remove diode D6302 + D6314

**\*\*MODS ON YOUR OWN RISC. DON'T BLAME ME!\*\***

73 Marcus PA2DB

